



SMT AG  
 Frohwiesstrasse 43  
 CH-8630 Rüti  
 Tel: +41 79 400 3810  
 Fax: ++41 55 66 30  
 Mail: info@smtec-ag.ch  
 www.smte-ag.ch

## M60 - BACnet Object List

Object	#	Value	Description	R/W	Default
BI	0	1-On , 0-Off	DI.1-DI.4 - Alarm Input	R	
	1	1-On , 0-Off	DI.2-DI.5 - Feedback AHU Off	R	
	2	1-On , 0-Off	DI.3-DI.6 - Reset/Clear	R	
BO	0	1-On , 0-Off	BO.1-BO.4 - Fan Output	R	
	1	1-On , 0-Off	BO.2-BO.5 - Error/Alarm	R	
	2	1-On , 0-Off	BO.3-BO.5 - Dampers Open/Close	R	
AV	0	0....180 Sec	DI.1-DI.4 - Alarm Input - On Delay	R/W	0
	1	0....180 Sec	DI.2-DI.5 - Feedback AHU Off - On Delay	R/W	0
	2	0....180 Sec	DI.3-DI.6 - Reset/Clear - On Delay	R/W	0
	3	960-1920-3840-7680	BaudRate	R	
	4	1..2	Zone Number	R	
	5	804121/122	Device Instant	R/W	
BV	0	1-On , 0-Off	DI.1-DI.4 - Alarm Input - NO/NC	R/W	0-N.Open
	1	1-On , 0-Off	DI.2-DI.5 - Feedback AHU Off - NO/NC	R/W	0-N.Open
	2	1-On , 0-Off	DI.3-DI.6 - Reset/Clear - NO/NC	R/W	0-N.Open
	3	1-On , 0-Off	Dip Switch 1 - Alarm All Zone	R	
	4	1-On , 0-Off	Dip Switch 2 - Zone Application Fire or Smoke	R	
	5	1-On , 0-Off	Alarm All Zone	R/W	0
MV	0	9600-19200-38400-76800	BaudRate	R	